



24/48/96 zone wire-free system operation

Arming

- Home:* Press 2 + code*
- Away:* Press 3 + code*
- Silent Arming:* Press 2 + code* + 5 for home
Press 3 + code* + 5 for away

Disarming

Press 1 + code*

Bypass

To arm system while any door or window (protected by a contact sensor) is open:
Press 2 + code* + # + code for home
Press 3 + code* + # + code for away

Status/Alarm Memory

Press * + code* for short status report
Press * + code* + * for long status report

Sensors

To identify which sensor activated the alarm follow the status/alarm memory instructions outlined above

Panic Button

Press the following buttons at the same time for 2 seconds:
A + 1 for Police
B + 4 for Emergency
C + 7 for Fire

Should you activate a panic alarm in error please wait for our call and do not engage your phone line. If we are unable to confirm that the alarm is false the relevant emergency service will be dispatched and in some cases charges may apply.

Please ensure you close all exterior doors and windows before setting your alarm